

Comant CI 509

SIGNAL COUPLER

CI 509 COUPLER - MARKER BEACON

Comant's two-through-hole-mount style coupler with BNC ports. Separates a single Marker Beacon antenna signal into two Marker Beacon signals. Designed for Marker Beacon only coupling applications. Suitable for internal aircraft mounting.

APPLICATIONS

Internal Aircraft Mounting
Warranty: 1 year
Always consult your installation shop for best application. See full disclaimer (Page 7) for more information.

FREQUENCIES COVERED

75 MHz (VHF - Marker Beacon)

SPECIFICATIONS

Electrical

Frequency	75 +/- .15 MHz
VSWR	1.5:1 Max
Isolation	20 dB Max
Insertion Loss	0.5 dB Max
Impedance	50 Ohms

Mechanical

Weight	0.20 lb.
Height	0.88 in.
Construction	Die Cast Aluminium
Finish	Aluminium
Connector	BNC (female)

Environmental

N/A	Internal Mounting
-----	-------------------

Federal Specifications

FAA TSO	C35d
---------	------

